

T-39-31

## 2.6 IGBT Module Range with Soft and Fast (SFD) Free-Wheeling Diodes

In order to maintain switching losses to minimal, improving Free Wheeling Diodes, (FWD), is essential and Hitachi's version of this is the Soft and Fast Recovery (SFD) Free Wheeling Diode. Basically, improvements have been achieved in the following key requirements.

- High speed ... small recovery time,  $t_r$
- Low loss ... small reverse-peak current,  $I_{rp}$
- Low noise ... small rate of charge of recovery current,  $di/dt$

Ultimately reducing your energy losses,  $Q_{rr}$ .

## 2.7 IGBT Modules Electrical Characteristics

Voltage Series	Type Number	Absolute Maximum Ratings					Typical Electrical Characteristics															
		Package	V <sub>CES</sub> (V)	V <sub>GES</sub> (V)	I <sub>C</sub> (A)	P <sub>C</sub> (W)	V <sub>CE(sat)</sub> (V)	C <sub>ies</sub> (pF)	t <sub>r</sub> (μs)	t <sub>on</sub> (μs)	t <sub>f</sub> (μs)	t <sub>off</sub> (μs)	t <sub>rr</sub> (μs)									
600V	MBN200A6	Single Arm	600	± 20	300	1200	2.5	18000	0.35	0.45	0.3	0.85	0.3									
	MBN400A6				400	1300																
	MBM50A6	Single Phase (Dual Pack)	600	± 20	50	250	3	2400	0.3	0.35	0.3	0.55	0.15									
	MBM75A6				75	325		3700														
	MBM100A6				100	400		4500														
	MBM150A6				150	600		7400														
	MBM200A6				200	730		9000														
	MBM300A6				300	1000		17000														
	MBB50A6				Three Phase (Six Pack)	600		± 20						50	250	3	2700	0.3	0.35	0.3	0.55	0.15
	MBB75A6													75	300		3700					
	MBB100A6	100	400	4500																		
	1200V	MBN200F12	Single Arm	1200	± 20	200	1200	3	19000	0.4	0.5	0.4	1	0.3								
MBN300F12		300				1700	33000															
MBM50F12		Single Phase (Dual Pack)	1200	± 20	50	400	3	4800	0.4	0.5	0.4	1	0.3									
MBM75F12					75	8900																
MBM100F12					100	700		9300														
MBM150F12					150	800		18000														
MBB50F12		Three Phase (Six Pack)	1200	± 20	50	-	-	-	-	-	-	-										